Filter-and-Sum Beamforming

ECE 6279: Spatial Array Processing
Spring 2011
Lecture 8

Prof. Aaron D. Lanterman

School of Electrical & Computer Engineering
Georgia Institute of Technology
AL: 404-385-2548
<lanterma@ece.gatech.edu>

Copyright 2011 Aaron Lanterman

Where We Are in J&D

- **Lecture material drawn from:**
  - –Sec. 4.3 (all)



Copyright 2011 Aaron Lanterman

Temporal Filtering

- **Filter the signal collected by each sensor in time**

$$y_m(t) = \{h_m(\cdot) *_t f(\vec{x}_m, \cdot)\}(t)$$
$$= \int_{-\infty}^{\infty} h_m(\tau) f(\vec{x}_m, t-\tau) d\tau$$

- **Then do delay-and-sum beamforming on the filtered signals, using techniques from past two lectures**

$$z(t) \equiv \sum_{m=0}^{M-1} w_m y_m(t - \Delta_m)$$

- **Choosing $h_m(t)=\delta(t)$ gives straight delay-and-sum beamforming**

Copyright 2011 Aaron Lanterman

Why Filter in Time?

- **Focus on frequency range of interest**
- **Reduce noise and interference in unwanted frequency bands**
- **In digital implementations, need antialiasing filter before A/D converters**
- **If you have a statistical model for the signal and the noise, you can design a Wiener filter (see ECE6254 class and textbook)**

Copyright 2011 Aaron Lanterman

Temporally Filtered Signal at Sensor

The usual: try a monochromatic plane wave!

$$f(\vec{x}_m,t)=\exp\{j(\omega^0 t-\vec{k}^0\cdot\vec{x}_m)\}$$

$$y_m(t)=\int_{-\infty}^{\infty}h_m(\tau)f(\vec{x}_m,t-\tau)d\tau$$

$$=\int_{-\infty}^{\infty}h_m(\tau)\exp\{j[\omega^0(t-\tau)-k^0\cdot\vec{x}_m]\}d\tau$$

$$=\exp\{j(\omega^0 t-\vec{k}^0\cdot\vec{x}_m)\}\times \underbrace{\int_{-\infty}^{\infty}h_m(\tau)\exp(-j\omega^0\tau)d\tau}_{H_m(\omega^0)}$$

Copyright 2011 Aaron Lanterman

(Temporal Filter)-and-Sum Beamforming

$$y_m(t)=H_m(\omega^0)\exp\{j(\omega^0 t-\vec{k}^0\cdot\vec{x}_m)\}$$

$$z(t)\equiv\sum_{m=0}^{M-1}w_m y_m(t-\Delta_m)$$

$$=\sum_{m=0}^{M-1}w_m H_m(\omega^0)\exp\{j(\omega^0[t-\Delta_m]-\vec{k}^0\cdot\vec{x}_m)\}$$

$$=e^{j\omega^0 t}\underbrace{\sum_{m=0}^{M-1}w_m H_m(\omega^0)\exp\{-j(\omega^0\Delta_m+\vec{k}^0\cdot\vec{x}_m)\}}_{\text{Wavenumber-frequency response}\rightarrow H(\vec{k}^0,\omega^0)}$$

Copyright 2011 Aaron Lanterman

Identical Temporal Filters (1)

$$z(t)=\exp(j\omega^0 t)H(\vec{k}^0,\omega^0)$$

where $H(\vec{k}^0,\omega^0)=\sum_{m=0}^{M-1}w_m H_m(\omega^0)\exp\{-j(\omega^0\Delta_m+\vec{k}^0\cdot\vec{x}_m)\}$

- **Notice if** $H_m(\omega)=H_0(\omega)$

  then $H(\vec{k}^0,\omega^0)=H_0(\omega^0)\sum_{m=0}^{M-1}w_m\exp\{-j(\omega^0\Delta_m+\vec{k}^0\cdot\vec{x}_m)\}$

Copyright 2011 Aaron Lanterman

Identical Temporal Filters (2)

- **If** $H_m(\omega)=H_0(\omega)$ **and we beamform on a planewave with slowness vector** $\vec{\alpha}$

$$H(\vec{k}^0,\omega^0)=H_0(\omega^0)\sum_{m=0}^{M-1}w_m\exp\{-j(\omega^0\Delta_m+\vec{k}^0\cdot\vec{x}_m)\}$$

$$\Delta_m=-\vec{\alpha}\cdot\vec{x}_m$$

$$=H_0(\omega^0)\sum_{m=0}^{M-1}w_m\exp\{j(\omega^0\vec{\alpha}-\vec{k}^0)\cdot\vec{x}_m\}$$

$$=H_0(\omega^0)W(\omega^0\vec{\alpha}-\vec{k}^0)$$

Copyright 2011 Aaron Lanterman

Identical Temporal Filters (3)

- If $H_m(\omega) = H_0(\omega)$ and we beamform on a planewave with slowness vector $\vec{\alpha}$

$$H(\vec{k}^0, \omega^0) = H_0(\omega^0) W(\omega^0 \vec{\alpha} - \vec{k}^0)$$

- If $H_0(\omega^0) = 1$, i.e. no filtering, we get

$$H(\vec{k}^0, \omega^0) = W(\omega^0 \vec{\alpha} - \vec{k}^0)$$

which is the old delay-and-sum result

Copyright 2011 Aaron Lanterman

Quick Question and Answer

- Question: To avoid needing *m* filters, why not just beamform first, then apply the *H*(*ω*) filter?

$$H(\vec{k}^0, \omega^0) = H_0(\omega^0) W(\omega^0 \vec{\alpha} - \vec{k}^0)$$

- Answer: filter first to avoid unwanted signals eating up the dynamic range of your A/D converters
  - Temporally filter first
  - Then beamform

Copyright 2011 Aaron Lanterman

Spatial Filtering

- Suppose now we filter in space

$$y_m(t) = \{h_m(\cdot) *_{\vec{x}} f(\cdot, t)\}(\vec{x}_m)$$
$$= \int_{-\infty}^{\infty} h_m(\vec{\chi}) f(\vec{x}_m - \vec{\chi}, t) d\vec{\chi}$$

- Usually we don't do this deliberately - occurs due to the nature of the given sensors
- Let's study the filter-and-sum beamformer with spatial filtering:

$$z(t) \equiv \sum_{m=0}^{M-1} w_m y_m(t - \Delta_m)$$

Copyright 2011 Aaron Lanterman

Spatially Filtered Signal at Sensor

$$f(\vec{x}_m, t) = \exp\{j(\omega^0 t - \vec{k}^0 \cdot \vec{x}_m)\}$$

$$y_m(t) = \int_{-\infty}^{\infty} h_m(\vec{\chi}) f(\vec{x}_m - \vec{\chi}, t) d\vec{\chi}$$

$$= \int_{-\infty}^{\infty} h_m(\vec{\chi}) \exp\{j(\omega^0 t - \vec{k}^0 \cdot [\vec{x}_m - \vec{\chi}])\} d\vec{\chi}$$

$$= e^{j(\omega^0 t - \vec{k}^0 \cdot \vec{x}_m)} \underbrace{\int_{-\infty}^{\infty} h_m(\vec{\chi}) \exp(j\vec{k}^0 \cdot \vec{\chi}) d\vec{\chi}}_{H_m(\vec{k}^0)}$$



Copyright 2011 Aaron Lanterman

(Spatial Filter)-and-Sum Beamforming

$$y_m(t) = H_m(\vec{k}^0)\exp\{j(\omega^0 t - \vec{k}^0 \cdot \vec{x}_m)\}$$

$$z(t) \equiv \sum_{m=0}^{M-1} w_m y_m(t - \Delta_m)$$

$$= \sum_{m=0}^{M-1} w_m H_m(\vec{k}^0)\exp\{j(\omega^0[t - \Delta_m] - \vec{k}^0 \cdot \vec{x}_m)\}$$

$$= e^{j\omega^0 t}\underbrace{\sum_{m=0}^{M-1} w_m H_m(\vec{k}^0)\exp\{-j(\omega^0\Delta_m + \vec{k}^0 \cdot \vec{x}_m)\}}$$

Wavenumber-frequency response $H(\vec{k}^0,\omega^0)$

Copyright 2011 Aaron Lanterman

Identical Spatial Filters (1)

$$z(t) = \exp(j\omega^0 t)H(\vec{k}^0,\omega^0)$$

where $H(\vec{k}^0,\omega^0) = \sum_{m=0}^{M-1} w_m H_m(\vec{k}^0)\exp\{-j(\omega^0\Delta_m + \vec{k}^0 \cdot \vec{x}_m)\}$

- Notice if $H_m(\vec{k}) = H_0(\vec{k})$

  then $H(\vec{k}^0,\omega^0) = H_0(\vec{k}^0)\sum_{m=0}^{M-1} w_m \exp\{-j(\omega^0\Delta_m + \vec{k}^0 \cdot \vec{x}_m)\}$

Copyright 2011 Aaron Lanterman

Identical Spatial Filters (2)

- If $H_m(\vec{k}) = H_0(\vec{k})$ and we beamform on a planewave with slowness vector $\vec{\alpha}$

$$H(\vec{k}^0,\omega^0) = \qquad \Delta_m = -\vec{\alpha} \cdot \vec{x}_m$$

$$H_0(\vec{k}^0)\sum_{m=0}^{M-1} w_m \exp\{-j(\omega^0\Delta_m + \vec{k}^0 \cdot \vec{x}_m)\}$$

$$= H_0(\vec{k}^0)\sum_{m=0}^{M-1} w_m \exp\{j(\omega^0\vec{\alpha} - \vec{k}^0) \cdot \vec{x}_m\}$$

$$= H_0(\vec{k}^0)W(\omega^0\vec{\alpha} - \vec{k}^0)$$

Copyright 2011 Aaron Lanterman

Identical Spatial Filters (3)

- If $H_m(\vec{k}) = H_0(\vec{k})$ and we beamform on a planewave with slowness vector $\vec{\alpha}$

$$H(\vec{k}^0,\omega^0) = H_0(\vec{k}^0)W(\omega^0\vec{\alpha} - \vec{k}^0)$$

- If $H_0(\vec{k}^0) = 1$, i.e. no filtering, we get

$$H(\vec{k}^0,\omega^0) = W(\omega^0\vec{\alpha} - \vec{k}^0)$$

which is the old delay-and-sum result

Copyright 2011 Aaron Lanterman

Spatiotemporal Filtering

- **Might filter in both space and time!**

$$y_m(t) = \{h_m * f\}(\vec{x}_m, t)$$
$$= \int_{-\infty}^{\infty}\int_{-\infty}^{\infty} h_m(\vec{\chi},\tau) f(\vec{x}_m - \vec{\chi}, t-\tau) d\vec{\chi} d\tau$$

- **By now we can guess the-filter and-sum beamformer output will look like**

$$z(t) = \exp(j\omega^0 t) H(\vec{k}^0, \omega^0)$$

where $H(\vec{k}^0,\omega^0) =$

$$\sum_{m=0}^{M-1} w_m H_m(\vec{k}^0,\omega^0) \exp\{-j(\omega^0 \Delta_m + \vec{k}^0 \cdot \vec{x}_m)\}$$

Copyright 2011 Aaron Lanterman

Idential Spatiotemporal Filters

- **If** $H_m(\vec{k},\omega) = H_0(\vec{k},\omega)$ **and we beamform on a planewave with slowness vector** $\vec{\alpha}$

$$H(\vec{k}^0,\omega^0) = H_0(\vec{k}^0,\omega^0) W(\omega^0\vec{\alpha} - \vec{k}^0)$$

Waveno-freq response of individual sensor

Waveno-freq response of beamformed array

Copyright 2011 Aaron Lanterman